

RE-EX Series

PA EXPANDER

General

RE-EX Series Expander operates with e'Scape. The consoles Expandable upto 128 zones with multiplication of 16zones. These console are user friendly system with option of zone selection for individual zone announcement and common announcement through microphones.




Features

- 24VDC Input voltage
- 19" 2U Rack mountable.
- Power ON, Communication, Fault Indications.
- RS-485 Communication with Indication.
- Membrane Keypad for user friendly operation.
- Zone Wise /Zone Group (Speaker line) Selection facility with LED indication.
- 100V audio output for Speaker.
- Plug Type Connector for easy wiring.
- Alarm activated on automatically announcing mode.
- Zones expansion in Multiple of 16

Specification

	Electrical Specification
<i>Input Voltage</i>	24VDC.
<i>Operating Temperature</i>	0 - 49° C/32-120° F.
<i>Relative Humidity</i>	93 ± 2% RH (non-condensing) at 32 ±2° C/90 ±3° F
<i>Audio output</i>	100V
<i>Max Switching Wattage</i>	500W
<i>Maximum Zone Output</i>	30W per Zone
<i>Audio Input</i>	From Main Console
<i>Communication Interface</i>	RS 485
<i>Dimensions(2U)</i>	(484 W X 88 H X 325D)mm

Dimensions



Compatible Device

Model	Description
e'Scape	PA Console
RE-LS6W	PA Wall Speaker
RE-LS6C	PA Ceiling Speaker

Ordering Information

Model	Description
RE-032EX	17-32 Zone PA Expander
RE-048EX	33-48 Zone PA Expander
RE-064EX	49-64 Zone PA Expander

India

RAVEL ELECTRONICS PVT LTD.,
150A, Electronics Industrial Estate,
Perungudi, Chennai – 96, India.
E-mail: sales@ravelfire.com; Web: www.ravelfire.com

UAE

RAVEL DMCC,
Unit No: G30, DMCC Business Center,
Level No 13, AG Tower, Dubai, UAE.
E-mail: sales@raveldmcc.com

USA

RAVEL AMERICAS INC.,
2855 NW 112th Ave ST#2 Miami,
Doral, Florida 33172, USA.
E-mail: sales.us@ravelfire.com

*Ravel reserve the right to change the specification without prior notice.