

RE-XP Series

PA EXPANDER

General

RE-XP Series Expander operates with Revac nx . The consoles Expandable upto 128 zones with multiplication of 16zones. These console are user friendly system with option of zone selection for individual zone announcement and common announcement through microphones.



Features

- 24VDC Input voltage
- 19" Rack mountable.
- Plug Type Connector for easy wiring.
- RS-485 Communication with Indication.
- Zone Wise (Speaker line) Selection facility with LED indication.
- Zones expansion in Multiple of 16.
- 100V audio output for Speaker.
- Power ON, Charger ON indications.
- Membrane Keypad for user friendly operation.
- Alarm activated on automatically announcing mode.

Specification

	Electrical Specification
<i>Input Voltage</i>	24VDC.
<i>Operating Temperature</i>	0 - 49° C/32-120° F.
<i>Relative Humidity</i>	93 ± 2% RH (non-condensing) at 32 ±2° C/90 ±3° F
<i>Audio output</i>	100V
<i>Max Wattage</i>	400W / 16Z
<i>Zone Output</i>	25W per Zone
<i>Audio Input</i>	From Main Console
<i>Communication Interface</i>	RS 485
<i>Dimensions(2U)</i>	(484 W X 88 H X 325D)mm

Dimensions



Revac nx

Compatible Device

Model	Description
REVAC_{nx}	PA Console
RE-LS6W	PA Wall Speaker
RE-LS6C	PA Ceiling Speaker

Ordering Information

Model	Description
RE-032XP	17-32 Zone PA Expander
RE-048XP	33-48 Zone PA Expander
RE-064XP	49-64 Zone PA Expander
RE-080XP	65-80 Zone PA Expander
RE-096XP	81-96 Zone PA Expander
RE-112XP	97-112 Zone PA Expander
RE-128XP	113-128 Zone PA Expander

India

RAVEL ELECTRONICS PVT LTD.,
150A, Electronics Industrial Estate,
Perungudi, Chennai – 96, India.
E-mail: sales@ravelfire.com; Web: www.ravelfire.com

UAE

RAVEL DMCC,
Unit No: G30, DMCC Business Center,
Level No 13, AG Tower, Dubai, UAE.
E-mail: sales@raveldmcc.com

USA

RAVEL AMERICAS INC.,
2855 NW 112th Ave ST#2 Miami,
Doral, Florida 33172, USA.
E-mail: sales.us@ravelfire.com