$\mathcal{M}omitI-\mathcal{R}\mathcal{P}$ Analogue Addressable Fire Alarm Repeater Panel



Product Overview

The MonitI-RP repeater panel is a compact remote unit for Ravel-MonitI Intelligent Analogue Addressable fire Alarm panel. It repeats all the indications of FACP in standalone Panel. It has (40X4) 160 character LCD Display. This repeater is connected to MonitI FACP using RS 485 communication network. Any communication fault or any loss in communication due to cable fault is indicated in this repeater panel. The display parameters can be selected individually to suit the requirement of each remote area.

Features:

- · Complies EN54.
- 160 (40X4) character LCD Display.
- RS 485 communication for Repeater.
- · One Programmable form C relay for fire.
- Extensive built in transient protection.
- · Common fire, fault LED indication.

Electrical Specification:

Primary Power

120 / 220VAC + 10% -15%, 60 / 50 Hz.

Standby Power

12v D.C (1 No of 12v, 4.5Ah Sealed Lead acid battery).

Operating Condition

Operating Temperature $0 - 49^{\circ}$ C/32-120° F. Relative Humidity $93 \pm 2\%$ RH (non-condensing) at $32 \pm 2^{\circ}$ C/90 $\pm 3^{\circ}$ F.

Charging Circuit

Charging Voltage 14.0VDC With current 200mA (Max).

Programmable Relays

Type : Form C No of Relays : 1

Relay Contact Rating : 2A @ 30 VDC,

0.5A @ 125VAC.

USB Port

Type : Type B

Version : 2.0

Mechanical Specification:

Dimensions : (200W X 140H X 50D)mm

Color : White / Red / Black

Construction : 18 Gauge (1.22 mm) CRCA sheet with powder-coated Finish

IP Rating : IP50

Cable Entry : 8xø19mm Knockout in top of the cabinet

Weight : 5Kg

Terminal Details:

0.0 tor	4	В	٧	В		NC	ON	CO
USB 2. Connec	RS 485	nt &		RS 485 Input		Program. Relay		•





Compatible Devices:

MODELS	DESCRIPTION
MonitI	Analogue Addressable Fire Alarm Control Panel

Ordering Information:

MODELS	Description		
MonítI-RP-W/B/R	Analogue Addressable Fire Alarm Repeater Panel		

Note:

W - White Color; R - Red Color; B - Black Color

India:

RAVEL ELECTRONICS PVT LTD.,

(An ISO 9001 Certified Company)
150A, Electronics Industrial Estate, Perungudi, Chennai - 96 .India.
E-Mail: marketing@ravelfire.com; Web: www.ravelfire.com

United Kingdom:

RAVEL ELECTRONICS LTD.,

Unit 11, Chancel Industrial Estate, Newhall street, Willenhall WV13 1NX, West Midlands, United Kingdom. E-mail: info@ravelfire.co.uk; Web: www.ravelfire.co.uk